

The Data Book Project

DatasheetArchive.com has launched an ambitious effort to digitize thousands of obsolete data books and technical manuals, making them searchable via the DatasheetArchive website.

Scroll down to see the scanned document.

| 型名 | 社名 | 用途 | 構造 | f MHz | 最大定格 | | | | | 電気的特性 (Ta=25°C) | | | | | | | | | | | | | | | | | |
|--------------|-----|---------------|-----|----------|-------------|-------|-------------|-----------|------|-----------------|----------------------------------|------------------------|----------------------------------|----------------------------------|------------------------|--------------------------------------|-------|------------------------|-----------------------|--------------------------------|--------------------------------|------------------------|-----------------------|-------|----|------|--|
| | | | | | V*** (V) | 区分*** | Vgs* (V) | I* (A) | 区分* | Pd/Pch (W) | I _{gss} (max) (A) | V _{gs} (V) | I _{gss} (min) (A) | I _{gss} (max) (A) | V _{gs} (V) | V _{gs(off)} (min) (V) | | V _{gs} (V) | I _p (A) | I _p (min) (S) | g _m (typ) (S) | V _{ps} (V) | I _p (A) | | | | |
| | | | | | | | | | | | | | | | | (max) | (V) | | | | | | | | | | |
| 2SJ299(L)(S) | 日立 | HS PSW | MOS | P E | -20 | DSS | ±20 | S | -5 | D | 20 | ±10μ | ±16 | | -0.1m | -16 | -1 | -2.5 | -10 | -1m | 3.5 | 5.5 | -10 | -3 | | | |
| 2SJ300 | 日立 | HS PSW | MOS | P E | -20 | DSS | ±20 | S | -10 | D | 12 | ±10μ | ±16 | | -0.1m | -16 | -1 | -2.5 | -10 | -1m | 6 | 9 | -10 | -5 | | | |
| 2SJ317 | 日立 | SW PA | MOS | P E | -12 | DSS | ±7 | S | ±2 | D | 1 | ±5μ | ±6.5 | | -1μ | -8 | -0.4 | -1.4 | -5 | -100μ | 1 | 2.3 | -5 | -1 | | | |
| 2SK11 | 東芝 | DC/LF A, Chop | J | N D | -20 | GDS | | | | | 10m | G | 100m | -1n | -10 | 0.3m | 6.5m | 10 | -0.5 | -6 | 10 | 0.1μ | 0.7m | | 10 | IDSS | |
| 2SK12 | 東芝 | DC/LF A, Chop | J | N D | -20 | GDS | | | | | 10m | G | 100m | -0.1n | -10 | 0.45m | 5m | 10 | -0.65 | -4.5 | 10 | 0.1μ | 0.8m | | 10 | IDSS | |
| 2SK13 | 東芝 | DC/LF A | J | N D | -12 | GDS | | | | | 10m | G | 100m | -0.1n | -10 | 0.45m | 5m | 10 | -0.65 | -4.5 | 10 | 0.1μ | 0.8m | | 10 | IDSS | |
| 2SK15 | 東芝 | DC/LF LN A | J | N D | -20 | GDS | | | | | 10m | G | 100m | -0.1n | -10 | 0.45m | 5m | 10 | -0.65 | -5 | 10 | 0.1μ | 0.8m | | 10 | IDSS | |
| 2SK16(H) | 日立 | Hi-Imp A | J | N D | | | -20 | S | | | 10m | G | 100m | -1n | -6 | 0.5m | 7m | 6 | -0.5 | -5 | 6 | 0.1μ | 1m | 3m | 6 | IDSS | |
| 2SK17 | 東芝 | LF A | J | N D | -20 | GDS | | | | | 10m | G | 100m | -1n | -10 | 0.3m | 6.5m | 10 | -0.5 | -6 | 10 | 0.1μ | 0.7m | 2m | 10 | IDSS | |
| 2SK18 | 東芝 | DC | J | N D | -40 | GDS | | | | | 10m | G | 200m | | | 0.45m | 2.8m | 10 | -0.65 | -3.5 | 10 | 0.1μ | 0.8m | | 10 | IDSS | |
| 2SK18A | 東芝 | DC | J | N D | -40 | GDS | | | | | 10m | G | 200m | | | 0.45m | 2.8m | 10 | -0.65 | -3.5 | 10 | 0.1μ | 0.8m | | 10 | IDSS | |
| 2SK19TM | 東芝 | FM/VHF RF | J | N D | -18 | GDO | | | | | 10m | G | 200m | -10n | -1 | 3m | 24m | 10 | -1.2 | | 10 | 1μ | | 7m | 10 | IDSS | |
| 2SK23A-8 | ㊦ | DC/VHF RF | J | N D | -27 | GDO | -9 | O | | | 10m | G | 250m | -10n | -6 | 2.7m | 12.1m | 10 | -0.45 | -3.85 | 10 | 30μ | 2.7m | | 10 | IDSS | |
| 2SK23A-9 | ㊦ | DC/VHF RF | J | N D | -40 | GDO | -9 | O | | | 10m | G | 250m | -10n | -6 | 2.7m | 12.1m | 10 | -0.45 | -3.85 | 10 | 30μ | 2.7m | | 10 | IDSS | |
| 2SK24 | 三洋 | LF A, AM RF | J | N D | -40 | GDS | -40 | O | | | 10m | G | 100m | -10n | -10 | 0.6m | 24m | 10 | | -6 | 10 | 10μ | 1.5m | | 10 | IDSS | |
| 2SK25 | 三洋 | FM RF/MIX | J | N D | -18 | GDS | -18 | O | | | 10m | G | 100m | -100n | -10 | 0.6m | 24m | 10 | | -7.2 | 10 | 10μ | | 6m | 10 | IDSS | |
| 2SK30 | 東芝 | LF A | J | N D | -50 | GDS | | | | | 10m | G | 100m | -1n | -30 | 0.3m | 6.5m | 10 | -0.4 | -5.0 | 10 | 0.1μ | 1.5m | | 10 | IDSS | |
| 2SK30ATM | 東芝 | LF LN A | J | N D | -50 | GDS | | | | | 10m | G | 100m | -1n | -30 | 0.3m | 6.5m | 10 | -0.4 | -5.0 | 10 | 0.1μ | 1.2m | | 10 | IDSS | |
| 2SK33 | 三菱 | FM/VHF RF | J | N D | -20 | GDO | | | | | 10m | G | 150m | -100n | -1 | 2.5m | 20m | 10 | -1 | -8 | 10 | 10μ | 4.5m | 7m | 10 | IDSS | |
| 2SK34 | 三菱 | LF LN A | J | N D | -50 | GDO | | | | | 10m | G | 150m | -10n | -10 | 0.3m | 12m | 10 | -0.3 | -6.0 | 10 | 10μ | 1.0m | 3m | 10 | IDSS | |
| 2SK37 | NEC | FM RF/MIX | J | N D | -20 | GDO | -15 | O | | | 10m | G | 100m | -10n | -10 | 0.5m | 6m | 5 | -0.3 | -4.5 | 5 | 10μ | 1.5m | 2m | 5 | 0.5m | |
| 2SK38 | 三菱 | 煙感知器, DC | MOS | N DE | 20 | DSX | ±10 | O | | | 20m | D | 100m | -1p | -10 | 0.4m | 5m | 10 | | -9 | 10 | 10μ | 0.5m | 0.8m | 10 | 1m | |
| 2SK38A | 三菱 | 煙感知器, DC | MOS | N DE | 20 | DSX | ±10 | O | | | 20m | D | 100m | -1p | -10 | 0.1m | 7m | 10 | | -5 | 10 | 10μ | 1m | 1.5m | 10 | 1m | |
| 2SK39 | ㊦ | C-MIC | J | N | -20 | GDO | | | | | | | -0.25n | -0.1 | | | | | | | | | 0.09m | | 9 | | |
| 2SK39A | ㊦ | C-MIC | J | N | -20 | GDO | -0.5 | O | 0.5m | G | 10m | | | -0.25n | -0.1 | | | | | | | | | 0.11m | | 9 | |
| 2SK40 | 日立 | LF LN A | J | N D | -50 | GDS | -50 | S | | | 10m | G | 100m | -10n | -30 | 0.6m | 6.5m | 15 | -0.4 | -5.0 | 15 | 0.1μ | 1m | | 15 | | |
| 2SK41 | 三洋 | FM RF/MIX | J | N D | -18 | GDS | | | | | 10m | G | 200m | -10n | -1 | 0.6m | 24m | 10 | | | | | | 7m | 10 | IDSS | |
| 2SK41(旧) | 三洋 | FM RF/MIX | J | N D | -18 | GDO | | | | | 10m | G | 150m | -10n | -1 | 0.6m | 24m | 10 | | | | | | 7m | 10 | IDSS | |
| 2SK42 | ㊦ | FM/AM RF | J | N D | -10 | GDO | | | | | 10m | S | 50m | | | 1m | 5m | 4 | -0.3 | | 4 | 100μ | 3.5m | 5.5m | 4 | IDSS | |
| 2SK43 | ㊦ | LF LN A | J | N D | -30 | GDO | -30 | O | | | 5m | G | 300m | -1n | -15 | 0.9m | 14.3m | 10 | -0.18 | -1.49 | 10 | 30μ | 6.3m | | 10 | IDSS | |

| 電 気 的 特 性 (Ta=25°C) | | | | | | | | | | | | | コンブリ メンタリ | 外 形 | 備 考 | 型 名 |
|----------------------|----------------------|------------|------------|-----|-----|------|------|-------------------------|------|------|---------------------------|---------------------|--------------|-----------------|---------------|-----|
| Cis (typ) (pF) | Crs (typ) (pF) | Vgs (V) | Vps (V) | NF | | f | Rg | Rps(ON) (max) (Ω) | Vgs | Ip | その他特性 | 測定条件 | | | | |
| | | | | typ | max | (Hz) | (Ω) | (Ω) | (V) | (A) | | | | | | |
| 840 | 280 | 0 | -10 | | | | | 0.13 | -10 | -3 | ton=90ns, toff=190nstyp | ID=-3A, VGS=-10V | 150 | GDS, 暫定 | 2SJ299(L) (S) | |
| 1300 | 500 | 0 | -10 | | | | | 0.08 | -10 | -5 | ton=146ns, toff=335nstyp | ID=-5A, VGS=-10V | 363 | SDG | 2SJ300 | |
| | | | | | | | | 0.7 | -2.2 | -0.5 | ton=590ns, toff=2350nstyp | ID=-0.2A, VGS=0 | 295 | GDS | 2SJ317 | |
| 3 | | -10 | 0 | | | | | | | | | | 2 | SGDC | 2SK11 | |
| 3 | | -10 | 0 | | 3 | 1k | 1M | | | | | | 2 | SGDC | 2SK12 | |
| 2.3 | | -10 | 0 | | 2 | 1k | 1M | | | | | | 2 | 代替2SK30ATM | 2SK13 | |
| 3 | | -10 | 0 | | 3 | 1k | 10k | | | | VN(P.P)=4μVmax | Rg=10kΩ, Δf=5~50Hz | 2 | SGDC | 2SK15 | |
| 9 | 2 | -1 | 6 | | | | | 350typ | 0 | | | | 3 | SGD* | 2SK16(H) | |
| 4 | 1.2 | 0 | 0 | | 1 | 1k | 1M | | | | | | 7 | SGD, 代替2SK30ATM | 2SK17 | |
| 4.5 | 2 | -10 | 0 | | | | | | | | ΔVGS/ΔTa=100μV/°Cmax | Ta=0~60°C, ID=0.2mA | 19 | Dual FET | 2SK18 | |
| 4.5 | 2 | -10 | 0 | | | | | | | | ΔVGS/ΔTa=100μV/°Cmax | Ta=0~60°C, ID=0.2mA | 19 | Dual FET | 2SK18A | |
| 4 | 0.45 | 0 | 0 | 2 | 3.5 | 100M | | | | | PG=20dBtyp | f=100MHz | 82A | DSG, 代替2SK192A | 2SK19TM | |
| 5 | 1.8 | 0 | 10 | 2 | | 100M | | | | | PG=18dBtyp | f=100MHz | 5 | SGD | 2SK23A-8 | |
| 5 | 1.8 | 0 | 10 | 2 | | 100M | | | | | PG=18dBtyp | f=100MHz | 5 | SGD | 2SK23A-9 | |
| 7.4 | 2 | | 10 | 1 | 2.5 | 1k | 1M | | | | NF=10dBmax | f=30Hz, Rg=1MΩ | 6 | DGS, 代替2SK44SP | 2SK24 | |
| | 1.1 | | 10 | 2.5 | | 100M | | | | | PG=21dBtyp | f=100MHz | 6 | DGS, 代替2SK41NP | 2SK25 | |
| 8.2 | 2.6 | 0 | 0 | 0.5 | 5.0 | 120 | 100k | | | | | | 7 | SGD, 代替2SK30ATM | 2SK30 | |
| 8.2 | 2.6 | 0 | 0 | 0.5 | 5.0 | 120 | 100k | | | | | | 82B | SGD | 2SK30ATM | |
| | 0.5 | 0 | 10 | 2.5 | | 100M | | | | | PG=20dBtyp | f=100MHz | 153A | DSG | 2SK33 | |
| 8 | 1.5 | 0 | 10 | 3.0 | 6.0 | 100 | 100k | | | | | | 153B | SGD | 2SK34 | |
| | 1 | 0 | 5 | | | | | | | | | | 10 | 代替2SK193 | 2SK37 | |
| | | 0 | 0 | | | | | | | | | | | | 2SK38 | |
| 8 | | 0 | 0 | | | | | | | | | | 11 | DS*G | 2SK38A | |
| | | | | | | | | | | | | | 12 | GSD | 2SK39 | |
| | | | | | | | | | | | S/N=50dBmin | f=1kHz, Vin=-60dBs | 12 | GSD, 代替2SK93 | 2SK39A | |
| 6.7 | 1.6 | 0 | 15 | 1 | 5 | 120 | 100k | | | | | | 13 | SGD | 2SK40 | |
| | 0.35 | 0 | 10 | 3.5 | | 100M | | | | | PG=22dBtyp | f=100MHz | 57A | DSG | 2SK41 | |
| | 0.35 | 0 | 10 | 3.5 | | 100M | | | | | PG=22dBtyp | f=100MHz | 14 | SGD, 代替2SK41 | 2SK41 (IE) | |
| | 0.085 | | 4 | 2.5 | | 100M | | | | | PG=12dBmin | f=100MHz | 15 | GSD | 2SK42 | |
| 13 | 2.4 | 0 | 10 | | | | | | | | NF=13nV/√Hz | f=1kHz, Rg=10kΩ | 16A | SGD | 2SK43 | |