

The Data Book Project

DatasheetArchive.com has launched an ambitious effort to digitize thousands of obsolete data books and technical manuals, making them searchable via the DatasheetArchive website.

Scroll down to see the scanned document.

Medium Power Amplifiers and Switches

TYPE NO.	POLARITY	CASE	MAXIMUM RATINGS			H _{FE}				V _{CE(SAT)}		f _T min (MHz)	Cob max (pF)	COMPLEMENTARY TYPE
			P _d (mW)	I _C (A)	V _{CEO} (V)	min	max	I _C (mA)	V _{CE} (V)	max (V)	I _C (A)			
BC119	N	TO-39	800	1	30	40	120	150	1	0.35	0.15	40	25	BC139
BC138	N	TO-39	800	1	30	35	—	100	10	1.5	1	40	25	—
BC139	P	TO-39	700	0.5	40	40	—	100	10	0.8	0.3	—	6+	BC119
BC140	N	TO-39	800	1.1	40	40	250 #	100	1	1	1	50	25	BC160
BC141	N	TO-39	800	1	60	40	250 #	100	1	1	1	50	25	BC161
BC142	N	TO-39	800	1	60	20	—	200	2	0.4	0.2	40	25	BC143
BC143	P	TO-39	800	1	60	20	—	300	1	0.6	0.2	60	20	BC142
BC144	N	TO-39	800	1	40	20	—	300	1	0.6	0.5	100+	20	—
BC160	P	TO-39	800	1	40	40	250 #	100	1	1	1	50	30	BC140
BC161	P	TO-39	800	1	60	40	250 #	100	1	1	1	50	30	BC141
BC185	N	TO-39	700	0.5	40	40	—	100	10	0.45	0.3	200	8	—
BC210	N	TO-18	450	0.7	25	20	120	150	1	—	—	100	8	—
BC211	N	TO-39	800	1	40	40	250 #	150	2	1	1	50	25	BC313
BC211A	N	TO-39	800	1	60	40	250 #	150	2	1	1	50	25	BC313A
BC215	P	TO-18	400	0.5	30	40	300 #	150	10	0.9+	0.5	150	8	—
BC223	N	TO-92F	360	0.4	30	100	450 #	50	2	0.3	0.1	100	10	—
BC231	P	TO-92B	625	0.4	30	100	450	50	5	0.25	0.05	100	10	BC232
BC232	N	TO-92B	625	0.4	30	100	450	50	5	0.3	0.1	100	10	BC231
BC284	N	TO-18	500	0.2	40	100	600	10	10	1	0.1	50	20	—
BC286	N	TO-39	800	1	60	20	180	500	2	1	1	150+	11+	BC287
BC287	P	TO-39	800	1	60	20	200	500	2	1	1	140+	18+	BC286
BC294	P	TO-39	600	0.6	60	100	300	150	10	0.4	0.15	100	—	—
BC297	P	TO-18	375	1	45	75	260 #	100	1	0.7	0.5	250+	8+	BC377
BC298	P	TO-18	375	1	25	75	260 #	100	1	0.7	0.5	250+	8+	BC378
BC300	N	TO-39	850	1	80	40	240 #	150	10	0.5	0.15	120+	10+	—
BC301	N	TO-39	850	1	60	40	240 #	150	10	0.5	0.15	120+	10+	BC303
BC302	N	TO-39	850	1	45	40	240 #	150	10	0.5	0.15	120+	10+	BC304
BC303	P	TO-39	850	1	60	40	240 #	150	10	0.65	0.15	100+	17+	BC301
BC304	P	TO-39	850	1	45	40	240 #	150	10	0.65	0.15	100+	17+	BC302
BC310	N	TO-39	800	1	70	40	—	200	1	0.4	0.2	90+	12+	BC311
BC311	P	TO-39	800	1	70	40	—	200	1	0.5	0.2	200+	12+	BC310
BC313	P	TO-39	800	1	40	40	250 #	150	2	1	1	50	30	BC211
BC313A	P	TO-39	800	1	60	40	250 #	150	2	1	1	50	30	BC211A
BC327	P	TO-92F	625	0.8	45	100	630 #	100	1	0.7	0.5	100+	14+	BC337
BC328	P	TO-92F	625	0.8	25	100	630 #	100	1	0.7	0.5	100+	14+	BC338
BC337	N	TO-92F	625	0.8	45	100	630 #	100	1	0.7	0.5	100+	10+	BC327
BC338	N	TO-92F	625	0.8	25	100	630 #	100	1	0.7	0.5	100+	10+	BC328
BC340	N	TO-39	800	0.5	40	40	250 #	50	5	0.4	0.15	100+	6.5+	BC360
BC341	N	TO-39	800	0.5	60	40	160 #	50	5	0.4	0.15	100+	6.5+	BC361
BC342	N	TO-39	800	1	60	20	—	500	10	0.8	0.3	100+	20	BC343
BC343	P	TO-39	800	1	60	20	—	500	10	0.8	0.3	100	20	BC342
BC344	N	TO-39	800	1	80	20	—	150	10	0.8	0.15	100	20	BC345
BC345	P	TO-39	800	1	80	20	—	150	10	0.8	0.15	100	20	BC344
BC360	P	TO-39	800	0.5	40	40	250 #	50	5	0.4	0.15	250+	6.5+	BC340
BC361	P	TO-39	800	0.5	60	40	160 #	50	5	0.4	0.15	250+	6.5+	BC341
BC368	N	TO-92B	800	1	20	85	375	500	1	0.5	1	65+	—	BC369
BC369	P	TO-92B	800	1	20	85	375	500	1	0.5	1	65+	—	BC368
BC376	P	TO-92F	625	1	20	60	340 #	200	1	0.5	0.5	—	—	—
BC377	N	TO-18	375	1	45	75	500	100	1	0.7	0.5	100	12	BC297
BC378	N	TO-18	375	1	25	75	500 #	100	1	0.7	0.5	100	12	BC298
BC381	P	TO-92F	625	0.2	25	60	—	2.5	5	0.25	0.05	100	10	—
BC387	N	TO-92F	310	0.6	30	40	300	100	1	0.5	0.1	200	10	BC388
BC388	P	TO-92F	310	0.6	30	40	300	100	1	0.5	0.1	200	10	BC387
BC425	N	TO-92F	500	0.5	60	20	250	100	10	0.25	0.1	50	4+	BC427
BC427	P	TO-92F	500	0.5	60	20	250	100	10	0.25	0.1	50	4.7+	BC425

H_{FE} groupings available + Typical value