

TYPE NO	CONSTRUCTION	PACKAGE & PINOUT	V _{DS}		I _D	T _J	P _{TOT}	V _{GS(OFF)} or V _{GS(TH)}		I _{DSS} or I _{D(ON)}	G _{FS}	R _{DS(ON)}	C _{ISS}	C _{RSS}	USE	MNF	SUBSTITUTE	
			MAX	MAX				MAX	MAX									MAX
2SK16HA	NJD	T072 Fk	20V	10mA	150C	100mWF	3Vmx	0.5/7mA	1/2.5mS			9P0		ALG	HIT	BFW12	2N4032	
2SK16HB	NJD	T072 Fk	20V	10mA	150C	100mWF	3Vmx	0.5/7mA	2/4mS			9P0		ALG	HIT	BFW12	2N5458	
2SK16HC	NJD	T072 Fk	20V	10mA	150C	100mWF	3Vmx	0.5/7mA	3/6mS			9P0		ALG	HIT	BFW61	2N3822	
2SK17	NJD	T092 A	20V	10mA	125C	100mWF	6Vmx	6.5mAmx	700pSmn			6P0		ALN	OBS	BF808	2N3685A	
2SK17-G	NJD	T092 A	20V	10mA	125C	100mWF	0.5/6V	2.6/6.5mA	0.7/2mS			4P0	1P2	ALN	TOS	BF244		
2SK17-0	NJD	T092 A	20V	10mA	125C	100mWF	0.5/6V	0.6/1.4mA	0.7/2mS			4P0	1P2	ALN	TOS	BF244		
2SK17-R	NJD	T092 A	20V	10mA	125C	100mWF	0.5/6V	300/750pA	0.7/2mS			4P0	1P2	ALN	TOS	BF244		
2SK17-Y	NJD	T092 A	20V	10mA	125C	100mWF	0.5/5V	1.2/3mA	0.7/2mS			4P0	1P2	ALN	TOS	BF244		
2SK18	NJD	T077 Fna	20V	3mA	150C	200mWF	3.5Vmx	3mAmx	0.8/3mS			6P0		FVG	TOS	BC264A	2N3685A	
2SK18A	NJD	T077 Fna	20V	3mA	150C	200mWF	3.5Vmx	3mAmx	0.8/3mS			6P0		FVG	TOS	BC264A	2N3685A	
2SK18-0	NJD	T077 Fna	40V	10mA	150C	200mWF	2.5Vmx	0.8/1.6mA	1/2.3mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK18-R	NJD	T077 Fna	40V	10mA	150C	200mWF	1.8Vmx	450/900pA	0.8/1.9mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK18-Y	NJD	T077 Fna	40V	10mA	150C	200mWF	3.5Vmx	1.4/2.8mA	1.3/3mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK18A-0	NJD	T077 Fna	40V	10mA	150C	200mWF	2.5Vmx	0.8/1.6mA	1/2.3mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK18A-R	NJD	T077 Fna	40V	10mA	150C	200mWF	1.8Vmx	450/900pA	0.8/1.9mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK18A-Y	NJD	T077 Fna	40V	10mA	150C	200mWF	3.5Vmx	1.4/2.8mA	1.3/3mS			6P0	2P5	DUA	TOS	2N5045-7		
2SK19	NJD	T098 C	8V	25mA	125C	200mWF	1.2/7V	7mA	3/24mA					OP65	FVG	TO5	BF256	2N5245
2SK19/B	NJD	T098 C	8V	25mA	125C	200mWF	1.2/7V	12/24mA	7mStp					OP65	FVG	TO5	BF256C	2N5247
2SK19/G	NJD	T098 C	8V	25mA	125C	200mWF	1.2/7V	6/14mA	7mStp					OP65	FVG	TO5	BF256B	2N5245
2SK19/Y	NJD	T098 C	18V	25mA	125C	200mWF	1.2/7V	3/7mA	7mStp					OP65	FVG	TO5	BF256A	2N5246
2SK19TM	NJD	T092 A	18V	10mA	125C	200mWF	1.2/3V	3/24mA	7mStp			4P0	OP45	FVG	TOS	BF244		
2SK23	NJD	S14 F	18V	20mA	100C	250mWF	4.9Vmx	16mAmx	2.7mSmn			5P0		ALG	SOY	BFW61	2N5459	
2SK23A	NJD	S14 F	18V	20mA	100C	250mWF	4.9Vmx	4mA	5/9mS			5P0		ALG	SOY	BFW61	2N5459	
2SK23A4	NJD	S14 F	18V	20mA	100C	250mWF	0.45/3.9V	2.7/12mA	2.7mSmn			5P0	1P8	FVG	SOY	2N3822		
2SK23A4-2	NJD	S14 F	18V	20mA	100C	250mWF	0.45/2.4V	2.7/5.5mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A4-3	NJD	S14 F	18V	20mA	100C	250mWF	2.75Vmx	4.5/7.7mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A4-4	NJD	S14 F	18V	20mA	100C	250mWF	3.3Vmx	6.3/9.9mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A4-5	NJD	S14 F	18V	20mA	100C	250mWF	3.85Vmx	8.1/12mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A5-2	NJD	S14 F	27V	20mA	100C	250mWF	0.45/2.4V	2.7/5.5mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A5-3	NJD	S14 F	27V	20mA	100C	250mWF	2.75Vmx	4.5/7.7mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A5-4	NJD	S14 F	27V	20mA	100C	250mWF	3.3Vmx	6.3/9.9mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A5-5	NJD	S14 F	27V	20mA	100C	250mWF	3.85Vmx	8.1/12mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A6-2	NJD	S14 F	40V	20mA	100C	250mWF	0.45/2.4V	2.7/5.5mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A6-3	NJD	S14 F	40V	20mA	100C	250mWF	2.75Vmx	4.5/7.7mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A6-4	NJD	S14 F	40V	20mA	100C	250mWF	3.3Vmx	6.3/9.9mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A6-5	NJD	S14 F	40V	20mA	100C	250mWF	3.85Vmx	8.1/12mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A8-2	NJD	S14 F	27V	20mA	100C	250mWF	0.45/2.4V	2.7/5.5mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A8-3	NJD	S14 F	27V	20mA	100C	250mWF	2.75Vmx	4.5/7.7mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A8-4	NJD	S14 F	27V	20mA	100C	250mWF	3.3Vmx	6.3/9.9mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A8-5	NJD	S14 F	27V	20mA	100C	250mWF	3.85Vmx	8.1/12mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A9-2	NJD	S14 F	40V	20mA	100C	250mWF	0.45/2.4V	2.7/5.5mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A9-3	NJD	S14 F	40V	20mA	100C	250mWF	2.75Vmx	4.5/7.7mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A9-4	NJD	S14 F	40V	20mA	100C	250mWF	3.3Vmx	6.3/9.9mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK23A9-5	NJD	S14 F	40V	20mA	100C	250mWF	3.85Vmx	8.1/12mA	2.7mSmn			5P0	1P8	FVG	SOY			
2SK24	NJD	T018 F	40V	25mA	125C	100mWF	6Vmx	0.6/24mA	1.5/12mS			7P4	2P0	ALN	SAN			
2SK24C	NJD	T018 F	40V	2mA	125C	100mWF	6Vmx	1.5mA	1.5/12mS			8P0		ALG	OBS	BFW13	2N3821	
2SK24D	NJD	T018 F	40V	5mA	125C	100mWF	6Vmx	3mA	1.5/12mS			8P0		ALG	OBS	BF347	2N3685	
2SK24E	NJD	T018 F	40V	10mA	125C	100mWF	6Vmx	6mA	1.5/12mS			8P0		ALG	OBS	BFW12	2N5457	
2SK24F	NJD	T018 F	40V	12mA	125C	100mWF	6Vmx	12mA	1.5/12mS			8P0		ALG	OBS	BC264	2N5459	
2SK24G	NJD	T018 F	40V	25mA	125C	100mWF	6Vmx	24mA	1.5/12mS			8P0		ALG	OBS	BF244	2N3819	
2SK25	NJD	T018 F	18V	24mA	125C	100mWF	7.2Vmx	0.6/24mA	6mS					1P1	FVG	SAN	BF245	
2SK30	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.3/6.5mA	1.5mSmn			16P	5P0	ALG	TOS	BF347	2N5458	
2SK30/G	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	2.6/7mA	1.5mSmn			16P	5P0	ALG	TOS	BC264A	2N5458	
2SK30/O	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.6/1.4mA	1.5mSmn			16P	5P0	ALG	TOS	BF347	2N3821	
2SK30/R	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	300/750pA	1.5mSmn			16P	5P0	ALG	TOS	BF347	2N3686	
2SK30/Y	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	1.2/3mA	1.5mSmn			16P	5P0	ALG	TOS	BFW12	2N3685	
2SK30A	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.3/6.5mA	1.2mSmn			16P	5P0	ALN	TOS	BF347	2N5458	
2SK30A/G	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	2.6/6mA	1.2mSmn			16P	5P0	ALN	TOS	BC264A	2N5458	
2SK30A/O	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.6/1.4mA	1.2mSmn			16P	5P0	ALN	TOS	BF347	2N3821	
2SK30A/R	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	300/750pA	1.2mSmn			16P	5P0	ALN	TOS	BF347	2N3686	
2SK30A/Y	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	1.2/3mA	1.2mSmn			16P	5P0	ALN	TOS	BFW12	2N3685	
2SK30ATM	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.3/6.5mA	1.2mSmn			16P	5P0	ALN	TOS	BF244		
2SK30ATM-G	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	2.6/6.5mA	1.2mSmn			16P	5P0	ALN	TOS			
2SK30ATM-O	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	0.6/1.4mA	1.2mSmn			16P	5P0	ALN	TOS			
2SK30ATM-R	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	300/750pA	1.2mSmn			16P	5P0	ALN	TOS			
2SK30ATM-Y	NJD	T092 A	50V	10mA	125C	100mWF	0.4/5V	1.2/3mA	1.2mSmn			16P	5P0	ALN	TOS			
2SK32	NJD	T092 A	35V	20mA	150C	300mWF	4Vmx	10mA	3mS			10P		ALG	NEC	BC264	2N3822	
2SK33	NJD	T092 C	20V	20mA	125C	150mWF	8Vmx	20mA	7mStp			3P5		FVG	MIT	BF810	2N5397	
2SK33-D	NJD	T092 C	20V	20mA	125C	150mWF	1/8V	2.5/6mA	7mStp			3P5	1P0	FVG	MIT	BF346		
2SK33-E	NJD	T092 C	20V	20mA	125C	150mWF	1/8V	5/12mA	7mStp			3P5	1P0	FVG	MIT			
2SK33-F	NJD	T092 C	20V	20mA	125C	150mWF	1/8V	10/20mA	7mStp			3P5	1P0	FVG	MIT			
2SK34	NJD	T092 A	30V	20mA	125C	150mWF	6Vmx	6mA	3mStp			6P0		ALN	MIT	BFW56	2N3684A	
2SK34-A	NJD	T092 A	30V	20mA	125C	150mWF	0.3/6V	300/800pA	1/3mS			8P0		ALG	MIT	BF244		
2SK34-B	NJD	T092 A	30V	20mA	125C	150mWF	0.3/6V	0.6/1.5mA	1/3mS			8P0		ALG	MIT			
2SK34-C	NJD	T092 A	30V	20mA	125C	150mWF	0.3/6V	1/3mA	1/3mS			8P0		ALG	MIT			