

| | | | | | | |
|--------------|------|---|------------|----------------|---------|---|
| 2 SC 3183 | Si-N | S-L, 900/800V, 0,2A, 25W, 15MHz | 17j | (BUX 85) | 17j | |
| 2 SC 3184 | Si-N | S-L, 900/800V, 0,5A, 30W, 15MHz | 17j | (BUX 85) | 17j | |
| 2 SC 3187 | Si-N | Vid, 300/300V, 0,1A, 0,75W, 140MHz | 7c | BF 420 A | 7c | |
| 2 SC 3189 | Si-N | TV-HA, hi-def, 250/100V, 7,5A, 50W | 17j | BU 406 | 17j | |
| 2 SC 3190 | Si-N | HF, 35V, 0,1A, 0,4W, 120MHz | 7c | BC 546, BF 959 | 7a, 7d | |
| 2 SC 3191 | Si-N | =2SC3190: 0,2W | 41c | BC 546, BF 959 | 7a, 7d | |
| 2 SC 3192 | Si-N | FM-ZF, 35V, 0,05A, 175MHz | 7c | BF 255 | 7d | |
| 2 SC 3193 | Si-N | =2SC3192: | 41c | BF 255 | 7d | |
| 2 SC 3194 | Si-N | FM-V, 40V, 0,02A, 550MHz | 7c | BF 255 | 7d | |
| 2 SC 3195 | Si-N | =2SC3194: | 41c | BF 255 | 7d | |
| 2 SC 3196 | Si-N | TV-ZF, re, 40V, 0,05A, 530MHz | 7c | BF 198 | 7d | |
| 2 SC 3197 | Si-N | TV-ZF, 30V, 0,05A, 660MHz | 7c | BF 198, BF 199 | 7d | |
| 2 SC 3198 | Si-N | Uni, ra, 60V, 0,15A, 0,4W, 130MHz | 7c | 2SC2632 | 7c(9mm) | |
| 2 SC 3199 | Si-N | =2SC3198: 0,2W | 41c | 2SC2632 | 7c(9mm) | |
| 2 SC 3200 | Si-N | NF, ra, 120V, 0,1A, 0,3W, 100MHz | 7c | 2SC2632 | 7c(9mm) | |
| 2 SC 3201 | Si-N | =2SC3200: 0,2W | 41c | 2SC2632 | 7c(9mm) | |
| 2 SC 3202 | Si-N | Uni, 35V, 0,5A, 0,3W, 300MHz | 7c | BC 337 | 7a | |
| 2 SC 3203 | Si-N | Uni, 35V, 0,8A, 0,6W, 120MHz | 7c | BC 337 | 7a | |
| 2 SC 3204 | Si-N | =2SC3203: 0,3W | 41c | BC 337 | 7a | |
| 2 SC 3205 | Si-N | NF-Tr/E, 30V, 2A, 1W, 120MHz | 7c(9mm) | 2SD1207 | 7c(9mm) | |
| 2 SC 3206 | Si-N | NF/Vid, 200V, 0,05A, 0,8W, 120MHz | 7c(9mm) | BF 420 A | 7c | |
| 2 SC 3207 | Si-N | NF/Vid, 300V, 0,1A, 0,9W, 70MHz | 7c(9mm) | 2SC3468 | 7c(9mm) | |
| 2 SC 3208 | Si-N | S-L, 300/300V, 0,15A, 100MHz | 17j | 2SC1505 | 17j | |
| 2 SC 3209 | Si-N | CTV-Vid-E, 300/300V, 0,2A, 1W, 50MHz | 9b | 2SC3468 | 7c(9mm) | |
| 2 SC 3210 | Si-N | S-L, 500/400V, 10A, 100W, <1/3,5µs | 16c | - | | |
| 2 SC 3211 | Si-N | S-L, 800/500V, 5A, 70W, <1/4µs | 16c | (BU 426 A) | 18j | 3 |
| 2 SC 3211 A | Si-N | =2SC3211: 900/500V, <1,2/4,2µs | 16c | (BU 426 A) | 18j | 3 |
| 2 SC 3212 | Si-N | S-L, 800/500V, 7A, 100W, <1/3,5µs | 16c | (BU 426 A) | 18j | 3 |
| 2 SC 3212 A | Si-N | =2SC3212: 900/500V, <1,2/3,7µs | 16c | (BU 426 A) | 18j | 3 |
| 2 SC 3215 | Si-N | S-L, 1200/800V, 10A, 125W, <1/5µs | 23a | BUW 13 A | 18j | |
| 2 SC 3225 | Si-N | hi-beta, lo-sat, 40V, 2A, 220MHz, B>500 | 7c(9mm) | 2SC3225 | 7c(9mm) | |
| 2 SC 3226 | Si-N | NF-Tr/E, 30V, 2A, 0,9W, 150MHz | 7c(9mm) | 2SD1207 | 7c(9mm) | |
| 2 SC 3227 | Si-N | NF-Tr/E, 80V, 0,4A, 0,8W, 100MHz | 7c(9mm) | 2SD1812 | 7c(9mm) | |
| 2 SC 3228 | Si-N | NF-Tr/E, 160/160V, 1A, 0,9W, 120MHz | 7c(9mm) | 2SD1812 | 7c(9mm) | |
| 2 SC 3229 | Si-N | NF/Vid-L, 300/300V, 0,05A, 95MHz | 13j | (BF 759) | 13h | 5 |
| 2 SC 3230 | Si-N | NF/S-L, 30V, 3A, 10W, 100MHz | 17j | (BD 243 C) | 17j | 8 |
| 2 SC 3231 | Si-N | NF/S-L, 200V, 4A, 40W, 8MHz, <3/9,5µs | 17j | (BU 406) | 17j | |
| 2 SC 3232 | Si-N | S-L, 900/400V, 6A, 80W, <0,5/4µs | 16j | BU 426 A | 18j | |
| 2 SC 3233 | Si-N | S-L, 500/400V, 2A, 20W, <1/3,5µs | 30j | (BUX 85) | 17j | 4 |
| 2 SC 3234 | Si-N | TV-VA-E, 150/150V, 1,5A, 25W, 4MHz | ≈15j | 2SD1138 | 17j | |
| 2 SC 3235 | Si-N | S-L, 500/400V, 2A, 20W, <1/3,5µs | ≈15j | BUX 85 | 17j | |
| 2 SC 3236 | Si-N | S-L, 500/400V, 5A, 60W, <1/3,5µs | ≈15j | BU 11 A | 17j | |
| 2 SC 3237 | Si-N | NF/S-L, 30V, 3A, 20W, 100MHz | ≈15j | (BD 243 C) | 17j | 8 |
| 2 SC 3238 | Si-N | NF/S-L, 160V, 1,5A, 25W, 100MHz | ≈15j | 2SC2344 | 17j | |
| 2 SC 3239 | Si-N | lo-sat, 60V, 5A, 25W, 120MHz | ≈15j | 2SC3258 | 17j | |
| 2 SC 3242(A) | Si-N | Uni, 20V, 2A, 0,9W, 80MHz | 7c(9mm) | 2SD1207 | 7c(9mm) | |
| 2 SC 3243 | Si-N | Uni, 60V, 1A, 0,9W, 120MHz | 7c(9mm) | 2SD1207 | 7c(9mm) | |
| 2 SC 3244 | Si-N | Uni, 100V, 0,5A, 0,9W, 130MHz | 7c(9mm) | 2SD1812 | 7c(9mm) | |
| 2 SC 3245 | Si-N | Uni, 120/120V, 0,1A, 0,9W, 200MHz | 7c(9mm) | 2SC2632 | 7c(9mm) | |
| 2 SC 3245 A | Si-N | =2SC3245: 150/150V | 7c(9mm) | 2SC2632 | 7c(9mm) | |
| 2 SC 3246 | Si-N | lo-sat, 30V, 1,5A, 0,9W, 130MHz, B>400 | 7c(9mm) | 2SC3225 | 7c(9mm) | |
| 2 SC 3247 | Si-N | lo-sat, 50V, 1A, 0,9W, 130MHz, B>600 | 7c(9mm) | (2SC3225) | 7c(9mm) | 7 |
| 2 SC 3248 | Si-N | Uni, 180/180V, 0,1A, 0,9W, 130MHz | 7c(9mm) | 2SC3468 | 7c(9mm) | |
| 2 SC 3249 | Si-N | Vid, 300/250V, 0,1A, 0,9W, 80MHz | 7c(9mm) | 2SC3468 | 7c(9mm) | |
| 2 SC 3250 | Si-N | Vid-E, 300/300V, 0,1A, 15W, 100MHz | 17o(B=case | (2SC1505) | 17j | 5 |
| 2 SC 3251 | Si-N | HF-L, 55V, 0,4A, 15W, 700MHz | 17f(E=case | - | | |