

Typ type	Art device	Bild figure	Ersatztyp replacement	Bild figure
CS 2,5-04...06	50Hz-Thy	17e	TAG 626/600	17e
CS 3-02...07	50Hz-Thy	17e	TAG 626/600	17e
CS 3,5-02...06	50Hz-Thy	17e	TAG 626/600	17e
CS 3,5-05FZ2	50Hz-Thy	13e	TAG 626/600	17e
CS 0014	Si-Di	31a	1N4148	31a
CS 0080	Si-Di	31a	1N4148	31a
CS 1245(F...T)	Si-N		BC 337	7a
CS 1312 F,G	Si-P	2a	BF 324	7a
CS 1312 H	Si-P	2a	BC 560	7a
CS 1312 I	Si-P	2a	BC 560	7a
CS 1506 F,G	Si-P	2a	BC 556	7a
CS 1508 E,G	Si-N	2a	BF 255	7d
CS 1509 E,F	Si-N	2a	BF 255	7d
CS 1655	Si-N	7c	BF 255	7d
CS 1659	Si-N	7c	BC 337	7a
CS 1660	Si-P	7c	BC 327	7a
CS 1702	Si-N		BC 337	7a
CS 1774	Si-N	7c	BC 546	7a
CS 1909	Si-N	2a	BC 337	7a
CS 1910	Si-P	2a	BC 327	7a
CS 1914(H)	Si-P	2a	BC 556	7a
CS 1978(A)	Si-N	7e	BC 337	7a
CS 5609	Si-N		BC 337	7a
CS 5610	Si-P		BC 327	7a
CS 6203 H,I	Si-P	7e	BC 560	7a
CS 6208	Si-N	2a	BC 337	7a
CS 6209	Si-P	2a	BC 327	7a
CS 6305(A)	Si-P	2a	BC 556	7a
CS 9003	Si-N	7	BC 546	7a
CS 9010	Si-N	7e	BC 546	7a
CS 9011(D...I)	Si-N	7e	BC 546	7a
CS 9012(D...I)	Si-P	7e	BC 327	7a
CS 9013(D...I)	Si-N	7e	BC 337	7a
CS 9014(A...C)	Si-N	7e	BC 550	7a
CS 9015(A...C)	Si-P	7e	BC 560	7a
CS 9016(D...H)	Si-N	7e	BF 255	7d
CS 9017	Si-N	7e	BF 255	7d
CS 9018(D...H)	Si-N	7e	BF 255	7d
CS 9020(G,H)	Si-P	7e	BF 324	7a

Typ type	Art device	Bild figure	Ersatztyp replacement	Bild figure
CS 9021	Si-N	7	BF 255	7d
CS 9022	Si-N	7	BC 546	7a
CS 9102(B)	Si-P		BC 640	7c
CS 9103(B,C)	Si-N		BC 639	7c
CS 9126	Si-N	7e	BC 546	7a
CS 9127	Si-P	7e	BC 556	7a
CSF 02 AM 1	F-Thy	7b	BRX 49	7a
CSF 02 AM 2	F-Thy	7b	BRX 49	7a
CSF 02 AM 4	F-Thy	7b	BRX 49	7a
CSF 02 AM 8	F-Thy	7b	BRX 49	7a
CSF 02 AM 10	F-Thy	7b	TAG 626/600	17e
CV 12(B...E)	Thy	13e	TAG 626/600	17e
CX 701	Si-N	17j	2SD1138	17j
CX 701 A	Si-N	17j	2SD1138	17j
CX 702	Si-N	17j	BU 406	17j
CX 702 A	Si-N	17j	BU 406	17j
CX 703	Si-N	7e	BF 259	2a
CX 703 A	Si-N	7e	BF 259	2a
CX 703 B	Si-N	7e	BF 259	2a
CX 704(A...C)	Si-N	17j	BD 243 C	17j
CX 705	Si-N	23a	2N3055	23a
CX 705 A	Si-N	23a	2N3055	23a
CX 754(A...C)	Si-P	17j	BD 244 C	17j
CX 901	Si-N	7e	-	
CX 904(B...E)	Si-N	7e	BC 550	7a
CX 906(A...D)	Si-N	7e	BC 337	7a
CX 908(B...D)	Si-N	7e	BC 337	7a
CX 917	Si-N	7e	BF 255	7d
CX 918	Si-N	7e	BF 198	7d
CX 954(B...E)	Si-P	7e	BC 560	7a
CX 956(A...D)	Si-P	7e	BC 327	7a
CX 958(B...D)	Si-P	7e	BC 327	7a
D				
D...	..-N		Japantypen->2SD...	
	Z.B./m.o. "0731"		= 2SD731	