

2 SB 733	Nec	Si-P	LF, 20/16V, 2A, 1W, >50MHz, sat<0,4V(1A)	{2SD773 9b		2SB892	7c(9mm)	2SA1704, 2SB892, 2SB926...927, 2SB1433
2 SB 734	Nec	Si-P	Uni, 60/50V, 1A, 1W, 80MHz	{2SD774 9b		2SB892	7c(9mm)	2SA1315, 2SA1429, 2SB1229
2 SB 736	Nec	Si-P	SMD, Uni, 60/50V, 0,3A, 100MHz	{2SD780 35a	SOT-23	BC 807	35a	BCW 68
2 SB 736 A		Si-P	=2SB736: 80/80V	35a	SOT-23			BCX 42
2 SB 736 AR		Si-P	=2SB736: 80/80V	35d	SOT-23			BCX 42R
2 SB 736 R		Si-P	=2SB736:	35d	SOT-23			BCW 68R
2 SB 737	Rhm	Si-P	LF, In, 50/40V, 0,3A, 0,25W, 100MHz	{2SD786 7c	TO-92	BC 560	7a	BC 416, BC 560, 2SA970, 2SA1136...1137,++
2 SB 738	Hit	Si-P	LF Out, 20/16V, 2A, 0,9W, 150MHz	{2SD787 7c(9mm)	TO-92L	2SB892	7c(9mm)	2SA1382, 2SB892, 2SB927, 2SB1312
2 SB 739		Si-P	=2SB738: 20/20V	{2SD788 7c(9mm)	TO-92L	2SB892	7c(9mm)	2SA1382, 2SB892, 2SB927, 2SB1312
2 SB 740	Hit	Si-P	LF Out, 70/50V, 1A, 0,9W	{2SD789 7c(9mm)	TO-92L	2SB1212	7c(9mm)	2SA1013, 2SA1315, 2SB647, 2SB1212
2 SB 741		Si-P	=2SB740: 70/70V	{2SD790 7c(9mm)	TO-92L	2SB1212	7c(9mm)	2SA1013, 2SA1315, 2SB647, 2SB1212
2 SB 742	Nec	Si-P	P, 20/16V, 2A, 10W	14h	TO-126	BD 238	14h	BD 176, BD 234, BD 330, BD 376, ++
2 SB 743	Nec	Si-P	P, 40/30V, 3A, 10W, 55MHz	{2SD793 14h	TO-126	2SB986	14h	BD 786, MJE 250...254, 2SB986
2 SB 744(A)	Nec	Si-P	P, 70/45(A=70/60)V, 3/5A, 10W, 45MHz	{2SD794 14h	TO-126	(BD 190) ⁸	14h	BD 788, BD 790, MJE 250...254
2 SB 745	Mat	Si-P	Uni, In, 35/35V, 50/200mA, 0,4W, 150MHz	{2SD661 9c		BC 560	7a	BC 214, BC 259, BC 309, BC 559, ++
2 SB 745 A		Si-P	=2SB745: 55/55V	9c		BC 560	7a	BC 416, BC 560, 2SA970, 2SA1136...1137,++
2 SB 746	Hit	Si-P	Uni, 25/20V, 0,5A, 0,4W, 260MHz	7c	TO-92	BC 327	7a	BC 327...328, BC 636, BC 638, BC 640, ++
2 SB 747	Mat	Si-P	P, 80/80V, 5A, 55W, 7MHz	{2SD812 17j	TO-220	BD 244 C	17j	BD 244 B, BD 540B, BD 544B, BD 952, ++
2 SB 748(A)	Hit	Si-P	P, 120/100V, 6A, 60W, 20(A=22)MHz	{2SD824 20j		2SA1295	20j	2SA1075...1076, 2SA1094, 2SB705(A,B), ++
2 SB 749(A)	Hit	Si-P	P, 120/120V, 7A, 80W, 20(A=22)MHz	{2SD825 20j		2SA1295	20j	2SA1075...1076, 2SA1094, 2SB705(A,B), ++
2 SB 750	Mat	Si-P-Darl+Di	P, 60/60V, 2A, 35W, hFE=1k...10k, 0,2/2µs	{2SD836 17j	TO-220	BD 902	17j	BD 716, BDW 24A, BDW 54A, BDW 64A, ++
2 SB 750 A		Si-P-Darl+Di	=2SB750: 80/80V	17j	TO-220	BD 902	17j	BD 718, BDW 24B, BDW 54B, BDW 64B, ++
2 SB 750 B		Si-P-Darl+Di	=2SB750: 100/100V	17j	TO-220	BD 902	17j	BDW 24C, BDW 54C, BDW 64C, ++
2 SB 751	Mat	Si-P-Darl+Di	P, 60/60V, 4A, 40W, hFE=1k...10k, 0,2/2µs	{2SD837 17j	TO-220	BD 902	17j	BD 646, BD 898, BDW 24A, BDW 64A, ++
2 SB 751 A		Si-P-Darl+Di	=2SB751: 80/80V	17j	TO-220	BD 902	17j	BD 648, BD 900, BDW 24B, BDW 64B, ++
2 SB 751 B		Si-P-Darl+Di	=2SB751: 100/100V	17j	TO-220	BD 902	17j	BD 650, BD 902, BDW 24C, BDW 64C, ++
2 SB 753	Tos	Si-P	100/80V, 7A, 40W, 10MHz, -3µs, sat<0,5V(4A)	{2SD843 17j	TO-220			2SA1293
2 SB 754	Tos	Si-P	P, 50/50V, 7A, 60W, 10MHz, sat<0,4V(4A)	{2SD844 18j	TO-3P	2SB754	18j	2SB827
2 SB 755	Tos	Si-P	P, 150/150V, 12A, 120W, 20MHz	{2SD845 20j		2SA1295	20j	2SA1076, 2SA1166(A), 2SA1187, 2SA1095, ++
2 SB 756	Tos	Si-P	P, 200/200V, 15A, 150W, 20MHz	{2SD846 20j		2SA1295	20j	2SA1169...1170, 2SA1295, 2SA1333
2 SB 757	Fjd	Si-P	P, 40/40V, 15A, 80W, <1/3µs	{2SD847 18j	TO-3P	BD 250	18j	BD 250, BD 546, BD 746, 2SA1292
2 SB 758	Nec	Si-P	P, 120/120V, 7A, 80W	19j				2SA986, 2SB618
2 SB 758 A		Si-P	=2SB758: 130/130V	19j				2SA986, 2SB618
2 SB 759	Mat	Si-P	Uni, 25/25V, 0,05A, 0,25W, 200MHz	40c		BC 556	7a	BC 213, BC 258, BC 308, BC 558, ++
2 SB 759 A		Si-P	=2SB759: 45/45V	40c		BC 556	7a	BC 212, BC 257, BC 307, BC 557, ++
2 SB 760	Mat	Si-P	P, 60/60V, 1/2A, 30W	{2SD855 17j	TO-220	BD 244 C	17j	BD 240A, BD 242A, 2SA748, 2SA1288, ++
2 SB 760 A		Si-P	=2SB760: 80/80V	17j	TO-220	BD 244 C	17j	BD 240B, BD 242B, 2SA985(A), 2SA1288, ++
2 SB 760 B		Si-P	=2SB760: 100/100V	17j	TO-220	BD 244 C	17j	BD 240C, BD 242C, 2SA985(A), 2SA1393, ++
2 SB 761	Mat	Si-P	P, 60/60V, 3/5A, 35W, 500/-ns	{2SD856 17j	TO-220	BD 244 C	17j	BD 242A, BD 536, BD 540A, BD 936, ++
2 SB 761 A		Si-P	=2SB761: 80/80V	17j	TO-220	BD 244 C	17j	BD 242B, BD 538, BD 540B, BD 938, ++
2 SB 761 B		Si-P	=2SB761: 100/100V	17j	TO-220	BD 244 C	17j	BD 242C, BD 540C, BD 938, 2SB633, ++
2 SB 762	Mat	Si-P	P, 60/60V, 4/8A, 40W, 300/-ns	{2SD857 17j	TO-220	BD 244 C	17j	BD 244A, BD 536, BD 540A, BD 950, ++
2 SB 762 A		Si-P	=2SB762: 80/80V	17j	TO-220	BD 244 C	17j	BD 244B, BD 538, BD 540B, BD 952, ++
2 SB 762 B		Si-P	=2SB762: 100/100V	17j	TO-220	BD 244 C	17j	BD 244C, BD 540C, BD 954, 2SB 633, ++
2 SB 763	Mat	Si-P	P, 60/60V, 5/10A, 60W	{2SD858 18j	TO-3P	BD 246 C	18j	BD 246A, BDV 92, 2SB775, 2SB688, ++
2 SB 763 A		Si-P	=2SB763: 80/80V	18j	TO-3P	BD 246 C	18j	BD 246B, BDV 94, 2SB775, 2SB688, ++
2 SB 763 B		Si-P	=2SB763: 100/100V	18j	TO-3P	BD 246 C	18j	BD 246C, BDV 96, 2SB775, 2SB688, ++
2 SB 764	Say	Si-P	Uni, 60/50V, 1/2A, 0,9A, 150MHz	{2SD863 7c(9mm)	TO-92L	2SB892	7c(9mm)	2SA1315, 2SB647, 2SB892, 2SB1041, ++
2 SB 765(K)	Hit	Si-P-Darl+Di	P, 120/120V, 3/6A, 30W, hFE=1k...20k 0,8/4,5µs, K: hi-rel Version	{2SD864 17j	TO-220	(BD 902) ⁷	17j	BDT 20, BDW 54D, BDW 64D
2 SB 766	Mat	Si-P	SMD, Uni, 30/25V, 1/1,5A, 200MHz	{2SD874 39b	SOT-89			BC 869, BCX 69, 2SA1203, 2SA1369
2 SB 766 A		Si-P	=2SB766: 60/50V	39b	SOT-89			BCX 52...53, 2SA1364, 2SB804, 2SB1025
2 SB 767	Mat	Si-P	SMD, Uni, 80/80V, 0,5/1A, 120MHz	{2SD875 39b	SOT-89			2SA1368, 2SA1661, 2SB789(A), 2SB805...806
2 SB 768	Nec	Si-P	Vid Out, 200/150V, 2/3A, 20W, 10MHz	{2SD1033 30j	TO-252	(2SB861) ⁶	17j	2SB928(A), (2SB630, 2SB861) ⁶
2 SB 772	Nec	Si-P	P, 40/30V, 3/7A, 10W, 80MHz, sat<0,5V(2A)	{2SD882 14h	TO-126	2SB772	14h	BD 786, MJE 250...254, 2SB744(A)
2 SB 773	Nec	Si-P	P, 100/100V, 6A, 70W	{2SD883 19j				2SA986, 2SB617, 2SB618, 2SB758(A)
2 SB 773 A		Si-P	=2SB773: 120/120V	19j				2SA986, 2SB617, 2SB618, 2SB758(A)
2 SB 774	Mat	Si-P	30/25V, hi-Ueb=15V, 0,1/0,2A, 0,4W, 150MHz	{2SD889 7c	TO-92	(BC 556)	7a	2SB894, 2SB1206, (BC 308, BC 558)
2 SB 775	Say	Si-P	P, 100/85A, 6/10A, 60W, 18MHz, 120/1650ns	{2SD895 18j	TO-3P	BD 246 C	18j	BD 246C, BDV 96, 2SA1141, 2SB688, ++
2 SB 776	Say	Si-P	P, 120/100V, 7/11A, 70W, 15MHz, 200/1500ns	{2SD896 18j	TO-3P	BD 246 C	18j	BD 246C, 2SA1146, 2SA1186, 2SB688, ++
2 SB 777	Fjd	Si-P	P, 80/80V, 10A, 80W, <1/3µs	{2SD907 18j	TO-3P	BD 246 C	18j	BD 246B, BDV 94, 2SA1141, 2SA1146, ++
2 SB 778		Si-P	=2SB777: 120/120V	18j	TO-3P	BD 246 C	18j	BD 246C, 2SA1141, 2SA1146, 2SB817, ++
2 SB 779	Mat	Si-P	SMD, 25/20V, 0,5/1A, 150MHz, sat<0,4V(0,5A)	{2SD813 35a	SOT-23	(BC 807) ¹⁷	35a	2SA1298, (BC 807...808, BCX 17...18) ¹⁷
2 SB 780	Mat	Si-P	Uni, 30/25V, 0,5A, 0,4W, 200MHz	{2SD919 40c		BC 327	7a	BC 327...328, BC 636, BC 638, BC 640, ++
2 SB 781	Hit	Si-P	P, 50/50V, 4A, 30W	17j	TO-220	BD 244 C	17j	BD 244, BD 536, BD 540A, BD 950, ++
2 SB 782		Si-P	=2SB781: 60/60V	17j	TO-220	BD 244 C	17j	BD 244A, BD 536, BD 540A, BD 950, ++
2 SB 783		Si-P	=2SB781: 80/80V	17j	TO-220	BD 244 C	17j	BD 244B, BD 538, BD 540B, BD 952, ++
2 SB 786	Rhm	Si-P-Darl	P, 40V, 2/3A, 5W, 150MHz, hFE=10000	{2SD944 14h	TO-126	(BD 680) ⁸	14h	BD 776, 2SB794...795, 2SB1008
2 SB 786		Si-P-Darl	=2SB786: Iso	14b	TO-126 Iso			2SB1310, 2SB1067
2 SB 787	Hit	Si-P	Uni, 120/80V, 0,05A, 0,625W	7e	TO-92	2SA1124	7c(9mm)	2SA872A, 2SA970, 2SA1285(A), 2SB716(A)++
2 SB 788	Mat	Si-P	Uni, In, 120/120V, 20/50mA, 0,4W, 150MHz	{2SD958 9c		2SA1124	7c(9mm)	2SA872A, 2SA970, 2SA1038, 2SA1136, ++
2 SB 789	Mat	Si-P	SMD, 100/100V, 0,5/1A, 120MHz	{2SD968 39b	SOT-89			BCX 53, 2SA1201, 2SA1368, 2SB804...806
2 SB 789 A		Si-P	=2SB789: 120/120V	39b	SOT-89			2SA1201, 2SA1661, 2SB806, 2SB1025
2 SB 790	Mat	Si-P	25/20V, 0,5/1A, 0,6W, 150MHz, sat<0,4V(0,5A)	{2SD969 9c		2SB892	7c(9mm)	2SB892, 2SB926...927, (BC 327...328) ¹⁷
2 SB 791(K)	Hit	Si-P-Darl+Di	P, 120/120V, 8/12A, 40W, hFE=1k...20k 0,5/3,1µs, K: hi-rel Version	{2SD970 17j	TO-220	(BD 902) ⁷	17j	BD652, BDT20, BDW74D, BDW54D, 2SB1343
2 SB 792	Mat	Si-P	SMD, Uni, In, 150/150V, 50/100mA, 200MHz	{2SD814 35a	SOT-23			-
2 SB 792 A		Si-P	=2SB792: 185/185V	35a	SOT-23			-
2 SB 793	Mat	Si-P	LF Drv, Out, 30/25V, 1/1,5A, 1W, 200MHz	{2SD973 9c		BC 640	7c	BC 327...328, BC 636, BC 638, BC 640, ++
2 SB 793 A		Si-P	=2SB793: 60/50V	9c		BC 640	7c	BC 327A, BC 636, BC 638, BC 640, ++
2 SB 794	Nec	Si-P-Darl+Di	P, 60/60V, ±1,5/3A, 10W, hFE=2k...30k	{2SD985 14h	TO-126	BD 680	14h	BD 678, BD 778, 2N6035...6036
2 SB 795		Si-P-Darl+Di	=2SB794: 80/80V	{2SD986 14h	TO-126	BD 680	14h	BD 680, BD 780, 2N6036
2 SB 796	Nec	Si-P	P, 200/200V, 10A, 200W, 14MHz	{2SD997 23a	TO-3	MJ 15016	23a	MJ 15016, 2SA909, 2SA1116...17, 2SB723
2 SB 798	Nec	Si-P	SMD, Uni, 30/25V, 1/1,5A, 110MHz	{2SD999 39b	SOT-89			BC 869, BCX 51, BCX 69, 2SA1203, 2SA1734
2 SB 799	Nec	Si-P	SMD, Uni, 60/50V, 0,7/1A, 120MHz	{2SD1000 39b	SOT-89			BCX 53, 2SA1364, 2SB1115(A), 2SB1122, ++
2 SB 800	Nec	Si-P	SMD, Uni, 80/80V, 0,3/0,5A, 100MHz	{2SD1001 39b	SOT-89			2SA1202, 2SA1368, 2SB767, 2SB789(A)
2 SB 801	Nec	Si-P	SMD, Uni, 45/45V, 1A, 80MHz	39b	SOT-89			BCX 51...53, 2SA1364, 2SB766A, 2SB1025
2 SB 802		Si-P	=2SB801: 60/60V	39b	SOT-89			BCX 52...53, 2SA1364, 2SB766A, 2SB1025
2 SB 803		Si-P	=2SB801: 100/100V	39b	SOT-89			BCX 53, 2SB804, 2SB1025
2 SB 804	Nec	Si-P	SMD, Uni, 100/80V, 1/1,5A, 80MHz	{2SD1005 39b	SOT-89			BCX 53, 2SA1416, 2SB803...04, 2SB1025...26
2 SB 805	Nec	Si-P	SMD, Uni, 100/100V, 0,7/1,2A, 75MHz	{2SD1006 39b	SOT-89			BCX53, 2SA1201, 2SB805...806, 2SB1025...25
2 SB 806		Si-P	=2SB805: 120/120V	{2SD1007 39b	SOT-89			2SA1201, 2SA1416, 2SB806, 2SB1025...26
2 SB 807	Mat	Si-P	SMD, LF, In, 150/150V, 0,1A, 200MHz	{2SD1009 39b	SOT-89			-